

Description

Device and method for regulating a transmission moment of
5 a continuous transmission signal

The invention relates to a device for controlling the
transmission time of a continuous transmission signal, in
particular of a transmission signal in a radio station.
10 The invention also relates to a method for controlling
the transmission time of a continuous transmission
signal.

In radio communications systems, for example the second
15 generation European Mobile Radio System GSM (Global
System for Mobile Communication), information (speech,
images or other data) is transmitted via a radio
interface with the aid of electromagnetic waves. The
radio interface relates to a connection between a base
20 station and one or more subscriber stations, in which
case the subscriber stations may be mobile stations or
fixed-position radio stations. The electromagnetic waves
are in this case emitted at carrier frequencies which are
in a frequency band specified for the respective system.
25 Frequencies in the frequency band around 2000 MHz have
been provided for future radio communications systems,
for example the UMTS (Universal Mobile Telecommunications
System) or other third generation systems. Two modes are
envisaged for this third mobile radio generation, with
30 one mode being referred to as FDD (Frequency Division
Duplex) operation, and the other mode being referred to
as TDD (Time Division Duplex) operation. Both modes
support a so-called CDMA subscriber separation method
(Code Division Multiple Access).

In the case of radio stations, particularly in the case of mobile stations for digital mobile radio, which, for example, support the GSM or UMTS standard, one major precondition is the capability to set the transmission time of the transmission signal. This is necessary in order to comply with the time references specified in the respective Standard.

For example, the transmission time of a mobile station is determined by the base station to which the mobile station has been synchronized. The transmission time of the mobile station is in this case corrected with respect to the data received from the base station. No information may be added to or removed from the transmission signal during the correction of this transmission time. This is associated with the requirement that only relatively minor corrections may be carried out to a symbol to be transmitted, and that large sudden time changes during the correction of the transmission time of the transmission signal must be avoided.

Furthermore, the rate of change with which a correction must be carried out is specified in the respective Standard, and must be complied with during the correction. In order to match the transmission time of the transmission signal to the nominal transmission time as well as possible, it is necessary to minimize the phase fluctuations in the signals, for example the so-called jitter, which refers in general to phase fluctuations.

German Laid-Open Specification DE 198 58 358 A1 discloses a method for time synchronization of radio stations in a radio communications system, in which case the radio stations may be base stations or moving mobile stations. The matching between the radio stations is carried out alternately. A second radio station receives transmissions from at least one first adjacent radio station via a radio interface. This second radio station uses the received transmissions to determine a reception time, and compares this reception time with the transmission time of its own transmissions. The result of the comparison is transmitted as synchronization

200201792WO

- 3 -

information to the first radio station, which once again
matches its own

200201792WO

- 2a -

transmission time to the transmission time of the second radio station, in the sense of the received synchronization information.

This method is complex, and both the transmission time and reception time must be changed and taken into account in each of the radio stations.

5 A further method for synchronization of the timebase of a receiving unit to the timebase of a transmitting unit in a telecommunications device is known from German Laid-Open Specification DE 195 25 426 C1. The receiving unit and the transmitting unit may each be a base station
10 or a mobile station, and may be used for signal transmission. The base station and mobile station timebases, which are generally not the same as one another, are continuously synchronized while a connection is in existence, in order to neutralize this discrepancy.
15 The transmitting unit transmits synchronization data, for example a synchronization word, for clock recovery, and data for synchronization of the receiving unit, in each channel time slot of a transmission frame in a data burst to the receiving unit. The data received in the receiving
20 unit is compared until the correct synchronization data is identified. The actual synchronization bit contained in the received synchronization word is determined, and its position is compared by means of a comparator with the nominal synchronization bit, which is used as a
25 reference bit in the receiving unit. If the two bit positions differ, the comparator produces an error signal. An error counting unit, which is connected downstream from the comparator, counts the error signals in a predetermined time period, which is governed by the
30 clock frequency for data burst transmission, and by the number of counting steps of a frame counting device. The time sequence of the error signals that are determined is a measure of the difference between the timebases of the receiving unit and of the transmitting unit. The
35 receiving unit uses the number of stored error signals to produce a

correction signal, which is used for synchronization during reception during a connection, or during a connection interruption in the event of reception failure.

The synchronization of the timebases of the receiving unit and of the transmitting unit in the known method is relatively complex, and relatively inaccurate.

- 5 The invention is based on the object of providing a device and a method of the type mentioned initially, in which the transmission time can be synchronized easily, highly accurately and highly reliably.
- 10 This object is achieved by a device which has the features of patent claim 1, and by a method which has the steps of patent claim 9.

A device according to the invention for controlling the
15 transmission time of a continuous transmission signal, that is to say of a signal without a data burst, in a transmitting/receiving unit, in particular a transmission signal from a radio station, has a correction unit which produces an output data signal. This correction unit is
20 electrically connected to a downstream sequence control unit, which produces a working clock signal which is applied to a downstream counter unit. The counter unit generates an actual transmission time signal. A control device, which is connected downstream from the counter
25 unit, uses the actual transmission time signal and an external nominal transmission time signal to produce a correction signal, which is applied to the correction unit in order to correct the actual transmission time.

- 30 This means that the transmission time can be set highly accurately and highly reliably. A further advantage is that the absolute transmission time can be set independently of the receiver assembly in the transmitting/receiving unit, explicitly only in the
35 transmitter assembly of the transmitting/receiving unit. Likewise, no readjustment of the frequency

of the system oscillator which is specified in accordance with the transmission standard is required, so that

there is no need for a change both to the transmission times and to the reception times of the signals, and there is hence no need for any change relating to this in the receiver.

5

In one preferred exemplary embodiment, the control device has a comparator unit, to whose inputs the actual transmission time signal and the nominal transmission time signal are applied, and the comparator unit output
10 signal is a difference signal which contains information about the discrepancy between the two transmission times. It is particularly advantageous for the comparator unit to be designed as a subtractor, for example as a comparator.

15

One particularly advantageous refinement is characterized in that the control device has a control unit, in particular a microprocessor, which is connected downstream from the comparison unit, with the difference
20 signal being applied to one input of the control unit, and with the control unit producing the correction signal as an output signal.

This means that the correction speed can be set such that
25 the correction is carried out within the time period specified by the respective standard, for example, UMTS. Furthermore, this makes it possible to match the data stream to be transmitted, that is to say the transmission signal, as accurately as possible and with as little
30 jitter as possible to the nominal transmission time, which is used as a reference and is known from the data received from another radio station, for example a base station. A further advantage is that this makes it possible to correct the actual transmission time without
35 any large sudden time changes, so that only small portions of a symbol to be transmitted are corrected.

The correction unit is preferably a fractional sampling rate converter unit with a variable conversion ratio.

In another advantageous embodiment of the invention, the correction unit is followed by a D/A converter, to one of whose inputs the clocked output data signal is applied, and to another of whose inputs a sampling clock signal
5 from a sampling clock source is applied. The D/A converter produces the analog transmission signal as an output signal.

The upstream control unit, which produces exclusively the
10 correction signal for the correction unit and thus does not influence the working clock of the D/A converter, means that the output clock from the D/A converter is virtually jitter-free, so that the transmission spectrum of the analog transmission signal complies with the
15 requirements in the respective standard.

A further preferred refinement is characterized in that a signal processing unit is connected downstream from the counter unit and from the sequence control unit, is
20 connected upstream of the correction unit and produces a transmission signal.

The control device may have a time control unit, which is connected upstream of the comparator unit and transmits
25 the external nominal transmission time signal to the comparator unit. A periodic start signal, whose period duration is defined by the respective radio signal, for example UMTS or GSM, is thus predetermined by this time control unit.

30 The apparatus has a number of clock domains, that is to say subsystems in the entire device which in general operate using different clocks and are thus not necessarily synchronized to one another. For example, the
35 control device is operated with a clock which is predetermined by the period duration of the nominal

transmission time signal by means of the time control unit. The device is simple, has little complexity, and is advantageously designed such that it can operate beyond these limits

of the various clock domains.

It is particularly advantageous for the transmitting/receiving unit to be a mobile station which,
5 in particular, supports one of the standards GSM or UMTS.

Further advantageous refinements of the device according to the invention are specified in the dependent claims.

10 The invention also includes a method for controlling the transmission time of a continuous transmission signal in a transmitting/receiving unit, in particular a transmission signal in a radio station. An internal actual transmission time signal is produced in the
15 transmitting/receiving unit, and is compared with an external nominal transmission time signal, which is derived from a received signal from the transmitting/receiving unit. A difference signal is produced from the discrepancy between the actual
20 transmission time and the nominal transmission time.

According to the invention, the actual transmission time is corrected only in the transmitting/receiving unit, in particular in the transmission assembly in the
25 transmitting/receiving unit. The correction is carried out in such a way that the discrepancy between the two transmission times, as contained in the difference signal, is minimized, the correction is carried out independently of the defined clock period of the basic
30 radio system, and the time period for the correction is set variably.

This allows the transmission time of the transmission signal to be adjusted relatively easily and quickly, and
35 allows synchronization of the transmission times with high accuracy and reliability.

It is particularly advantageous to set the time duration of the correction by the capability to vary the duration for which the conversion

ratio of a sampling rate converter unit differs from the normal value.

5 In one particularly preferred exemplary embodiment, the discrepancy between the transmission times is minimized by compressing or extending the input data signal in time.

10 In one advantageous embodiment of the method, this compression or extension of the input data signal is carried out by reducing or increasing the conversion ratio of the fractional sampling rate converter unit.

15 A correction signal is preferably applied to the fractional sampling rate converter unit in order to change the conversion ratio such that it is set either to a fixed value, which is predetermined for a steady state of the system, or to a value which corresponds to extension or compression of the input data signal.

20 One particularly advantageous refinement is characterized in that the value to which the conversion ratio is changed, the time period for which the changed conversion ratio is activated, and the time at which the changed conversion ratio is activated are contained and
25 transmitted as information in a single correction signal.

This means that the actual transmission time of the transmission signal can be matched as exactly as possible
30 and without jitter to the nominal transmission time, and that the correction of the transmission signal, as well as the transmission spectrum of the transmission signal, satisfy the conditions specified by the respective standard.

35 Further advantageous refinements of the method according

to the invention are specified in the dependent claims.

One exemplary embodiment of the invention will be explained in more detail in the following text with reference to schematic drawings, in which:

5 Figure 1 shows a block diagram of a device according to the invention;

Figure 2 shows signal profiles of an input data signal and of an extended output data signal; and

10

Figure 3 shows signal profiles of an input data signal and of a compressed output data signal.

A device according to the invention has a control device
15 (Figure 1). The control device 1 has a time control unit 11 with a downstream comparator unit 12 which, in the exemplary embodiment, is a subtractor 12. Furthermore, the control device 1 has a control unit 13, which is connected downstream from the comparator unit 12. The
20 control device 1, in particular the control unit 13, is electrically connected via a first input to a correction unit 2 which, in the exemplary embodiment, is a sampling rate converter unit. The sampling rate converter unit 2 is connected via a second input to an upstream signal
25 processing unit 3. A sampling clock source 4 is electrically connected to the sampling rate converter unit 2 at a third input. The sampling rate converter unit 2 has an electrical connection for a downstream sequence control unit 5 via a first output. The sequence control
30 unit 5 is also connected via a second input to the upstream sampling clock source 4. The output of the sequence control unit 5 is electrically connected firstly to one input of the signal processing unit 3 and secondly to one input of a counter unit 6. The output of this
35 counter unit 6 is electrically connected firstly to one input of the signal processing unit 3 and secondly to one

200201792WO

- 10 -

input

of

the comparator 12. The sampling rate converter unit 2 is followed by a D/A converter 7, whose second input is also connected to the

sampling clock source 4. Figure 1 illustrates only those components of a transmitter assembly in the transmitting/receiving unit which are significant to the invention.

5

The method of operation of the device for controlling the absolute transmission time of a continuous transmission signal will be explained in more detail in the following text. The time control unit 11 contains information about the nominal transmission time, which is predetermined by the basic system, for example UMTS or GSM. This information is transmitted by means of a signal to the transmitting/receiving unit. The time control unit 11 produces a periodic start signal, the nominal transmission time signal 101, which is applied to the subtractor 12. The period duration of the nominal transmission time signal 101 is in this case predetermined by the appropriate mobile radio system, for example UMTS or GSM. The sampling clock source 4 furthermore produces a sampling clock signal 301. The sampling clock should be regarded as the clock frequency at which a digital/analog (D/A) converter, in this case the D/A converter 7, is operated, or would have to be operated at in order to convert a signal from the digital domain to the analog domain.

This sampling clock signal 301 is applied to the sequence control unit 5. The sequence control unit 5 uses the sampling clock signal 301 and a control signal 201 that is produced by the sampling rate converter unit 2 to produce a working clock signal 202. The working clock is the clock used by the registers in the digital assemblies. The sampling clock is an undefined fractional ratio of the working clock, which is used as the basis for the signal processing unit 3. The working clock signal 202 is transmitted both to the signal processing

200201792WO

- 11 -

unit 3 and to the counter unit 6. The

counter unit 6 counts the working clock cycles contained in the working clock signal 202, for example by counting the edges of the working clock signal 202, and uses this to generate an actual transmission time signal 203. The
5 actual transmission time signal 203 is a periodically recurring

signal, which is generated by the counter unit 6 whenever a new transmission frame starts. This actual transmission time signal 203 is applied to one input of the comparator 12 and to one input of the signal processing unit 3.

5

The working clock is produced by the sequence control unit 5 in such a way that the signal processing unit 3 produces sample values, to be precise exactly at the required input-side sampling rate of the sampling rate converter unit 2. The sample values are transmitted to the sampling rate converter unit 2 with the aid of the data signal 204.

The subtractor 12 uses the transmission time signals 101 and 203 which are applied to its inputs to determine a time difference, which corresponds to the discrepancy between the actual transmission time and the nominal transmission time. This discrepancy is included as information in a difference signal 102 which is transmitted to the control unit 13. The difference signal 102 may be transmitted to the control unit 13 on the one hand by regular checking of the comparator 12 by the control unit 13. On the other hand, it may also be carried out by the control unit 13 triggering an interrupt request.

The magnitude of the discrepancy between the transmission times and the speed at which the discrepancy is changing are determined in the control unit 13 from the data information in the difference signal 102. The control unit 13 uses this information to produce a correction signal 103. The correction signal 103 contains information about the value to which a sampling rate ratio of the sampling rate converter unit 2 is changed, as well as the time period for which this changed sampling rate ratio is activated, and the time at which

200201792WO

- 12 -

this

activation

is

started. The expression sampling rate ratio means the conversion ratio of the fractional sampling rate converter unit 2, which is defined by the

ratio of the output sampling rate to the input sampling rate. This correction is used to minimize the discrepancy between the two transmission times. The correction is in this case carried out independently of the defined clock duration of the basic radio system, for example UMTS or DSM, and independently of the receiver assembly the correction is in this case carried out exclusively in the transmitter assembly in the mobile station, independently of the defined time duration for the basic radio system, for example, UMTS or GSM, and independently of the receiver assembly in the mobile station. The rate at which the correction is carried out is set variably, with the rate being set as a function of the value of the sampling rate ratio and of the time duration of the activated state in which this ratio is activated.

The correction signal 103 is transmitted from the control unit 13 to the sampling rate converter unit 2. The correction signal 103 is in this case transmitted from a clock domain of the transmitter assembly in the mobile station, in the bus clock domain (which is characterized by the control device 1 and is clocked with a clock duration which is predetermined by the time control unit 11) to a second clock domain in the transmitter assembly, the digital hardware clock domain. The control unit 13 thus predetermines the time at which the sampling rate converter unit 2 is driven.

The correction signal 103 is evaluated in the sampling rate converter unit 2, and the sampling rate converter unit 2 produces the clock control signal 201, which is used as the control signal for internal sequence control, as a function of the changed sampling rate ratio or conversion ratio. The digital hardware clock domain has a clock which is different, and is in general not synchronized to the clock for the bus clock domain.

The sampling rate ratio or conversion ratio of the sampling rate converter unit 2 has a permanently set ratio when it is in the steady state, during which no
5 correction is carried out for the time discrepancy between the transmission times.

If the sampling rate ratio is increased, then fewer data items are read in each time unit at the defined sampling clock rate. This means that the input data signal 204 which is transmitted from the signal processing unit 3 to the sampling rate converter unit 2 is extended, and that subsequent signal components of the input data signal 204 are shifted backwards in time. During production of the input data signal 204, the mean edge frequency of the working clock signal 202 is an integer multiple of the mean data rate of the input data signal 204. The clocked output data signal 302 from the sampling rate converter unit 2 is thus extended in comparison to the input data signal 204. In this case, in general, the input data signal 204 is clocked differently than the output data signal 302. The output data signal 302 is processed further in a third clock domain, the D/A converter clock domain in the mobile station, which in general uses a different clock than the bus and digital hardware clock domains.

20

When the sampling ratio is reduced, the output data signal 302 is compressed in comparison to the input data signal 204, and subsequent signal components are shifted forwards in time.

25

The changed sampling rate ratio remains activated until the discrepancy between the transmission times falls below a defined threshold value. Once this has been achieved, the correction signal 103 is deactivated, and the sampling ratio is once again permanently set to the value defined for the steady state.

The digital clocked output data signal 302 is transmitted to the D/A converter unit 7, which produces an analog continuous transmission signal 303 at the non-varying sampling clock rate 301. The phase angle of this

35

200201792WO

- 14 -

continuous analog transmission signal 303 matches the

phase angle predetermined by the nominal transmission time signal 101, with the phase angles of the two signals having at most a discrepancy which is within a defined tolerance band. This therefore also results in appropriate correction of the actual transmission time in comparison to the nominal transmission time as a reference time.

The maximum permissible discrepancy between the actual transmission time and the nominal transmission time of the transmission signal can thus be set very accurately by the device and the method. The remaining error is in this case generally dependent on the frequency at which the comparator 12 is checked by the control unit 13, and how the sampling rate converter unit 2 is driven by the control unit 13 by means of the correction signal 103.

The compression or extension of the input data signal 204 by the sampling rate converter unit 2 is carried out in such a way that no information is lost from or added to the input data signal 204.

It is possible for the actual transmission time signal 203 to contain, as information, the count of the counter unit 6 as the actual transmission time.

It is also possible to provide for the counter unit 6 to be periodically reset, and to be reset with the period duration of the nominal transmission time signal 101 when the mobile station is in the steady state.

Figure 2 shows an example of a signal profile of the input data signal 204. The time discrepancy between the actual transmission time with the time reference T_{new} and the nominal transmission time with the time reference T_{old}

200201792WO

- 15 -

is indicated by the time difference T_{diff} .

The sampling rate ratio is increased, as a result of which the input data signal 204 is changed in a corresponding manner, and the output data signal 302 has

an extended profile. As illustrated in the lower signal profile in Figure 2, the subsequent signal components are shifted backwards in time.

5 Figure 3 likewise shows an example of a signal profile of an input data signal 204 with the reference symbol for the time discrepancy T_{diff} , corresponding to that shown in Figure 2, and with the time references T_{old} , T_{new} of the transmission times. In this exemplary embodiment, the
10 sampling rate ratio has been reduced, so that the input data signal 204 has been changed in a corresponding manner, and the output data signal 302 has a compressed signal profile. The subsequent signal components are shifted forwards in time.

15

The device according to the invention and the method make it possible to easily set a transmission time for a continuous transmission signal. The correction for any discrepancy between the actual transmission time and the
20 nominal transmission time is carried out only in the transmission assembly in the mobile station, and is set with high accuracy and reliability over a number of clock domains within the transmission assembly. The correction is carried out independently of the system clock and of
25 the rate at which the discrepancy is changing, with the discrepancy between the transmission times being determined by a comparator unit, in particular a comparator 12, and the correction unit which is used for correction, in particular the sampling rate converter
30 unit 2, being controlled by the control unit 13. The correction is carried out in conjunction with the counter unit 6 and with the sequence control unit 5, in accordance with the requirements specified by the respective standard, for example UMTS or GSM.

35